

TACTILE PUSH SWITCHES

PTS-007-A1 H=4.3mm
PTS-007-B1 H=5.0mm
PTS-007-D1 H=7.0mm

- Rating: DC12V 50mA
- Stroke: 0.25mm
- Force: 160±50gf
- Life: 100,000 Cycles
- Carrier Tape: 1,000 Pcs

Circuit

Mounting Hole Layout

PTS-008-A1 H=4.3mm
PTS-008-B1 H=5.0mm

- Rating: DC12V 50mA
- Stroke: 0.25mm
- Force: 160±50gf
- Life: 50,000 Cycles
- Carrier Tape: 1,500 Pcs

Circuit

Mounting Hole Layout

PTS-032-B1

- Rating: DC12V 50mA
- Stroke: 1.0mm
- Force: 250±70gf
- Life: 50,000 Cycles
- Carrier Tape: 1,000 Pcs

Circuit

Mounting Hole Layout

PTS-046-A1 H=4.3mm
PTS-046-B1 H=5.0mm
PTS-046-D1 H=7.0mm
PTS-046-E1 H=9.5mm

- Rating: DC15V 20mA Max.
DC2V 10µA Min.
- Stroke: 0.25mm
- Force: 160±50gf
- Life: 1,000,000 Cycles
- Carrier Tape: 2,500 Pcs

Circuit

Mounting Hole Layout

PTS-047-A1 H=4.3mm
PTS-047-B1 H=5.0mm
PTS-047-D1 H=7.0mm
PTS-047-E1 H=9.5mm

- Rating: DC15V 20mA Max.
DC2V 10µA Min.
- Stroke: 0.25mm
- Force: 260±60gf
- Life: 100,000 Cycles
- Carrier Tape: 2,500 Pcs

Circuit

Mounting Hole Layout

PTS-048-A1 H=5.0mm
PTS-048-B1 H=5.0mm
PTS-048-C1 H=5.5mm
PTS-048-D1 H=6.1mm

- Rating: DC12V 5mA Max.
DC2V 10µA Min.
- Stroke: PTS-048-A1:1.0mm
PTS-048-B1:1.0mm
PTS-048-C1:1.2mm
PTS-048-D1:1.75mm
- Force: PTS-048-A1:80±40gf
PTS-048-B1:130±60gf
PTS-048-C1:250±60gf
PTS-048-D1:300±60gf
- Life: 100,000 Cycles
Except: PTS-048-A1: 1,000,000 Cycles
- Carrier Tape: 800 Pcs

Circuit

Mounting Hole Layout

PTS-113

- Rating: DC12V 50mA
- Stroke: 0.25mm
- Force: 160±50gf
- Life: 100,000 Cycles
- Carrier Tape: 700 Pcs

Circuit

Mounting Hole Layout

PTS-121-B

- Rating: DC2V 10µA ~ DC12V 50mA
- Stroke: 1.3mm
- Force: 250±60gf
- Life: 100,000 Cycles
- Carrier Tape: 2,500 Pcs

Circuit

Mounting Hole Layout